

CTS Economy Battery Bund Alarm



Code: SWS1019

| | |
|----------------------|--|
| Battery Requirements | 9v PP3 (Alkaline Only) |
| Operating Temps | -20c to +50c |
| Dimensions | 155 (L) x 95 (H) x 60 (D) mm |
| Colour | Light Grey RAL 7035 |
| IP Rating | IP55 |
| Float Material | Nylon Stem, NBR Float, PVC Cable, S/S Clip |
| S.G | 0.70 |
| Cap Mount | 1 1/2" BSP F |
| Cable Length | 5m |

INSTALLATION

Mount the box securely using 4 Non-Countersink screws – **Do not over-tighten** the fixings




Remove the single cross head cover screw (the other 3 are in an internal bag)



Turn the face of the alarm over to reveal the connections & battery holder

Pull off the sounder connector and wire the cable from the sounder into this and plug this connector on last before closing the lid. **Ensure that the RED wire connects to the + terminal.**



Pull off the float connector. Wire the probe cable to the float connector (its not polarity sensitive) and replace onto the board.



Insert the battery into the holder making sure the correct polarity of the connections, then push down at the base of the battery to secure in place.

The alarm will beep 3 times when the battery is connected.



OPERATION

The alarm is constantly checking the probe state, but to give a visual conformation to the user, a test function is provided.

Press and hold the **TEST** button. The red LED will **FLASH** 3 times and the sounder will **BEEP** 3 times—this indicates that the LED and sounder are functioning.

If the alarm activates then the LED will long **FLASH** and the sounder will long **BEEP** once every 2 seconds. This will continue until either:

1. The **MUTE** button is pressed for 3 secs
2. Or the float exits from the alarm condition

If the **MUTE** button is pressed then the red LED will continue to flash once every 3 seconds, but the sounder will be silenced.

The alarm will sound for in excess of 72 hours in full alarm mode, and with a new battery it will operate for more than 2 years in standby operation.

BATTERY LOW INDICATION

If the battery becomes discharged, the red LED will **FLASH** slowly and the sounder will **BEEP** similar to a smoke alarm. Please change the battery as soon as possible.